

ROWEMEISTERS - MARANTZ PM66 KI MODS 2008 CENTRE CHANNEL AMP

www.audiupgrades.co.uk

PSU

- FITTED SECOND KI TX (NOW RUNNING 2) VA approx 500VA
- REPLACED BRIDGE RECTIFIER (D801) WITH 4X MBR20 20A SCHOTTKY DIODES
- REPLACED C801 C802 WITH 63V 15,000uF BHC ALT AEROVOX
- REPLACED C717 C718 WITH 63V 470uF SILMICS
- REPLACED C719 WITH 63V 1000uF SILMIC
- REPLACED C720 WITH 16V 220uF BLACK GATE *STD*

INPUT

- FITTED QUALITY RCA TO AUX INPUT
- REPLACED C701 C702 WITH 250V 6.8uF MUNDORF *MKP* TYPE (audio in)
- REPLACED C705 C706 WITH 16V 100uF BLACK GATE *N* TYPE (feedback)
- REPLACED C709 C710 WITH 100pF SILVER MICA 1% TOL

OUTPUT

- REPLACED C751 C752 WITH 25V 100uF ELNA CEREFINE (ON BIAS CIRCUIT)
- REPLACED C753 C754 C755 C756 WITH 120pF SILVER MICA 1% TOL

NOTE – VOLTAGE TO OUTPUT IS NOW 46V (WAS 38V) THEREFORE THE OUTPUT WATTAGE SHOULD BE 80W INTO 8 ohm AND 100W INTO 4 ohm.

OTHER

- FITTED CHASSIS AND LID WITH DAMPING MATERIAL
- UNIT SITS ON OAK CONE FEET

EXTERNAL

- [KIMBER 4VS](#) SPEAKER CABLE BI-AMPED
- ATC [C3C](#) CENTRE SPEAKER

WEIGHT – 10.22 Kg

www.audiupgrades.co.uk

www.audiupgrades.co.uk/regs.shtml

www.audiupgrades.co.uk/rmcdmodlist.pdf